

Low Profile Mobile Antenna Mount with Toggle Joint

DESCRIPTION

- Can be used together with all Amphenol Procom mobile antenna whips provided with toggle joint.
- Installation possible everywhere on the car.
- Particularly well suited for rooftop-mounting because of very low internal protrusion and ability to be installed exclusively with access from the outside. Models with roof thickness from 2 mm to 7.5 mm mounting from the inside.
- Hole diameter: 21 mm.
- Mounting body made of stainless steel !
- Wide variety of antenna whips available in the frequency range up to 470 MHz.
- Choice between two connection principles:
 - Z-mount : FME-connection (supplied without cable).
 - ZP4-mount : Permanently attached 4 m cable terminated with FME-connector.
- Available in bright or black (black plastic parts for both versions).



SPECIFICATIONS

Electrical	
Frequency	0 - 470 MHz
Application	Low-profile mount for mobile antennas
Mechanical	
Installation Diameter	38 mm / 1.50 in.
Build-In Depth	10.5 mm
Materials	Stainless steel Bright or black chromed brass Weather- and shockproof plastics
Installation Torque	7.5 ±1 Nm
Colour	Black or bright and black
Whip Connection	Toggle joint (for wing screw or hat screw with key)
Height	400 mm / 15.75 in.
Weight	Z-version: Approx. 90 g ZP4-version: Approx. 230 g
Mounting	21 mm dia. hole (For roof thicknesses 2 mm up to 7.5 mm mounting hole should be 22 mm dia.)
Mounting Plate Thickness	Max. 2.0 mm (Models up to 7.5 mm on request)

ORDERING

Type	Product No.	Description
Z-Mount	130000396	Z-mount (bright) with FME-system
BZ-Mount	130000398	BZ-mount (black) with FME-system
ZP4-Mount	130000410	ZP4-mount (bright) with 4 m cable and FME-connector
BZP4-Mount	130000412	BZP4-mount (black) with 4 m cable and FME-connector
BZP5-Mount	130000408	BZP5-mount (black) with 5 m cable and FME-connector
Accessories - Roof Thickness		
Z-Mounting Adaptor	130002393	2 - 5 mm
Z-Mounting Adaptor	130002394	5 - 7.5 mm
Accessories - FME-Cables		
1 m FME(f) to FME(f) cable	130000437	
2 m FME(f) to FME(f) cable	130000447	
3 m FME(f) to FME(f) cable	130000457	
4 m FME(f) to FME(f) cable	130000466	
5 m FME(f) to FME(f) cable	130000474	
6 m FME(f) to FME(f) cable	130000483	
4 m FME(f) to FME(f) cable, white	110000064	
6 m FME(f) to FME(f) cable, white	110000066	
12 m FME(f) to FME(f) cable, white	110000068	
18 m FME(f) to FME(f) cable, white	110000069	
Accessories - FME-Connectors		
FME(f)-FME(f) Connector Adaptor	130000583	
FME(m)-P(m) (Prolongation) Connector Adaptor	130000565	
FME(m)-N(m) Connector Adaptor	130000571	
FME(m)-SMA(f) Connector Adaptor	130000578	
FME(m)-BNC(m) Connector Adaptor	130000566	
FME(m)-TNC(m) Connector Adaptor	130000569	
FME(m)-UHF(m) Connector Adaptor	130000572	
FME(m)-MiniUHF(m) Connector Adaptor	130000573	
FME(m)-MiniUHF(m)(Elbow) Connector Adaptor	130000582	
FME(m)-BNC(m)(Elbow) Connector Adaptor	130000580	
FME(m)-TNC(m)(Elbow) Connector Adaptor	130000581	
FME(m)-SMA(m) Connector Adaptor	130000577	

